

520015

GUARDIAN

WiFi Radio receiver

Open the outdoor gates and garage doors from anywhere



Compatible with any gate automation



2 outputs



Universal



Made in France



Environment friendly



Easy to install

OPERATION FROM ANYWHERE

This motor control receiver allows you to activate any motorized gate or garage door automation from your smartphone or tablet, without affecting compatibility with the original remote controls.



Works with



At Home

works with the Google Assistant





INSTALLATION



Contact 2 - Output

Contact 2 - Input

Contact 1 - Output

Contact 1 - Input

Line

Neutral

Typical installation: dry contact input 1 is connected to 2 leaves command, dry contact input 2 is connected to 1 leaf command (for pedestrians).

TECHNICAL CHARACTERISTICS

Max. power	1000 W
Features	Control garage door and gate opener
Connection	Wire 2 outputs
Cable cross-section	Up to 1.5 mm ²
Use	Indoor and outdoor
Operating T°	0 °C/+40 °C
Storage T°	-20 °C/+70 °C
Power supply	230 Vac/50 Hz
Average consumption	< 1 W
Installation	Close to the opener
Colour	Graphite black /red
Protection	IP20
Weight	65 g

RADIO PROTOCOL

Radio protocol	WiFi
Radio frequency	2,4 GHz
Protocol	802.11 b/g/n
Radio range	<ul style="list-style-type: none"> - Open area range: 80m - Masonry: 20m, through 3 walls max. - Reinforced concrete: 10 m, through 1 wall/floor max. - Drywall/wood: 30 m, through 5 walls max.



packing

2 years
guarantee



hotline



3345115200158